



PowerWalker VFI 1000 LE

Online UPS

1000VA Online UPS

2 IEC Outlet

USB Connection for monitoring

LED display to show UPS status



Item-No. 10120127









Monitoring

USB Port

2x IEC Outlets

Generator

Product Features

With true double-conversion design, PowerWalker VFI 1000 LE provides powerful and overall protection to your sensitive devices. It can accept wider input voltage for harsh environment. It's perfect protection for your servers and workstations.

- True double-conversion
- Output power factor 0.7
- Wide input voltage range (176-276 VAC)
- Input power factor correction 0.98







	`		LED Display	
Technical Details	•		LED Indicators	Load level, Battery level, Battery Mode, AC Mode, Fault
Product Features			Connections	
Capacity	1000VA / 700W		Communication	USB port
Input			Outlets	2x IEC
Phase	Single phase with ground			
Output				
AC Voltage Regulation (Batt. Mode)	± 2 %		Software & Syste	em Requirements
Frequency Range	46 ~ 54Hz or			<u> </u>
(Synchronized Range)	56 ~ 64Hz		Software	WinPower For details visit:
Frequency Range (Batt. Mode)	50Hz ± 0.1Hz or 60Hz ± 0.1Hz		Operating System	www.powerwalker.com/winpower.html
Current Crest Ratio	3:1		Other	1x USB port
Harmonic Distortion	≤ 4% THD (Linear Load) ≤ 7% THD (Non-linear Load)		Product Details	
	≤ 7% THD (Non-linear Load)		Dimensions	345mm x 144mm x 220mm
Waveform (Batt. Mode)		P	ur e S ine Wave	Black
Transfer Time			Weight	9.8kg
AC Mode to Batt. Mode	zero		Fan Control	Always on
Inverter to Bypass	4ms (Typical)		Noise Level	< 45dB at 1 meter
Efficiency			Model Code	VFI 1000 LE
AC Mode	86 %		Environment	
Battery Mode	80 %		Temperature	0°C − 40°C
Battery			Humidity	20 - 90% (non-condensing)
Туре	12V / 7.2Ah		Package Content	į
Quantity	2x		Package Content	PowerWalker VFI 1000 LE,
Recharge Time	5h to 90%		. usinge content	Software CD, USB cable, 2x IEC
Audio Indicators				output cables, power cord, printed
Battery Mode	Beep every 5sec		La sistia Data	manual
Low Battery		В	Logistic Data eep every second Giftbox Language	
Overload	Beep twice every second		Silloon Luliguage	<u> </u>
Fault	Continuously sounding		Manual Language	EN
	· •		BlueWalker Item-No.	10120124
		lt	erfi -N b. 10120502	4260074971798
			Warranty	24 Months (except battery)

Use UPS configurator on www.powerwalker.com for detailed backup time information.

Version: EN 17/04/2012

We reserve the right for technical changes and mistakes

Martin-Buber-Strasse 12 • D-41470 Neuss • Germany